



300V DIGITAL MULTIMETER

JEFDMM300V

- CAT III 300V Digital Multimeter
- 3.5 digit LCD display (max. reading 1999)
- Data hold function & overload protection
- Low battery indication
- Negative polarity indication
- Continuity and diode testing
- Battery testing: 1.5V / 9V / 12V
- Resistance measurements: Up to 2000K Ω
- Manufactured & tested to IEC 61010

- DC Voltage Range: 200m ~ 300V
- DC Current Range: 2000 μ ~ 10A
- AC Voltage: 200 ~ 300V
- Input Impedance: 1M Ω
- Resistance: 200 ~ 2000k Ω
- Continuity: <30 Ω
- Diode Testing: 2.8V (approx)
- Test Current: 1mA
- Battery Testing: 1.5V / 9V / 12V
- Overload Protection:
 - Both Fuses: ϕ 5x20mm
 - F1: Fuse, 250mA / 300V, Fast action
 - F2: Fuse, 10A / 300V, Fast action
- Power Supply: 1x 9V Battery
- Dimensions: 138 x 74 x 32mm
- Weight: 160g (inc. battery)



Jefferson[®]
PROFESSIONAL TOOLS & EQUIPMENT